

## **Product features:**

- Wide range of Output Power Options
- 300Hz output for High Speed Filming
- Compensation of Lamp Cable Volt Drop
- Pluggable Power Modules

## This is a recently revised design based on our 10kW pluggable power module system.

This means that the power components can be exchanged in a few minutes, ensuring your equipment is always ready for work. The ballast is capable of operating any lamp in the range 6kW through to 18kW and 300Hz operation comes as standard, so it's ready for High Speed shooting when needed.

The power circuits have been designed to tolerate huge voltage fluctuations to keep the product running under the harshest of power supply conditions.

PRODUCT SPECIFICATION			
Max Lamp Power	18000W	Output Power Options	18kW, 12kW, 9kW, 6kW
Output Frequency Options	Silent Mode, 100Hz, 300Hz, 1000Hz (9kW only)	Input Voltage Range	195-265V AC
<b>Current Draw</b>	81.7A @ 230V	Power Factor	>0.98
DMX Built In	Yes	Max Ambient Temperature	45°C / 113°F
Width	322mm / 12.7"	Height	442mm / 17.4" (without cart)
Length	483.5mm / 19"	Weight	42kg / 92lb (without cart)

## EB1812P 18kW/12kW/9kW/6kW Electronic Ballast

